

---

# NI-9264 and sbRIO-9264 Specifications

---

2024-06-08



# Contents

NI-9264 and sbRIO-9264 Specifications..... 3

# NI-9264 and sbRIO-9264 Specifications

## Connector Types

The NI-9264 has more than one connector type: NI-9264 with spring terminal and NI-9264 with DSUB. Unless the connector type is specified, NI-9264 refers to all connector types.

The NI-9264 with spring terminal is available in two types: push-in spring terminal and spring terminal. The push-in type spring terminal connector is black and orange. The spring terminal connector is black. NI-9264 with spring terminal refers to both types unless the two types are specified. Differences between the two types of spring terminal connectors are noted by the connector color.

## Definitions

**Warranted** specifications describe the performance of a model under stated operating conditions and are covered by the model warranty.

**Characteristics** describe values that are relevant to the use of the model under stated operating conditions but are not covered by the model warranty.

- **Typical** specifications describe the performance met by a majority of models.
- **Nominal** specifications describe an attribute that is based on design, conformance testing, or supplemental testing.

Specifications are **Typical** unless otherwise noted.

### Related information:

- [Software Support for CompactRIO, CompactDAQ, Single-Board RIO, R Series, and EtherCAT](#)

## Conditions

Specifications are valid for the range -40 °C to 70 °C unless otherwise noted. All voltages are relative to COM unless otherwise noted.

## Output Characteristics

Number of channels	16 analog output channels	
DAC resolution	16 bits	
Type of DAC	String	
Power-on output state	Channels off	
Startup voltage <sup>1</sup>	0 V	
Power-down voltage <sup>2</sup>	0 V	
<b>Output range</b>		
Nominal	±10 V	
Minimum	±10.35 V	
Typical	±10.5 V	

1. When the module powers on, a glitch occurs for 20  $\mu$ s peaking at 500 mV.
2. The power-down voltage peaks at 1.7 V, then exponentially discharges to 0 V in 200 ms. You can add a load to reduce peak voltage.

Maximum	±10.65 V
Current drive	±16 mA all channels maximum; ±4 mA per channel typical
Output impedance	2.0 Ω

**Table 1. Accuracy**

	Measurement Conditions	Percent of Reading (Gain Error)	Percent of Range <sup>3</sup> (Offset Error)
Calibrated	Maximum (-40 °C to 70 °C)	0.15%	0.15%
	Typical (25 °C)	0.05%	0.05%
Uncalibrated <sup>4</sup>	Maximum (-40 °C to 70 °C)	0.6%	1.0%
	Typical (25 °C)	0.2%	0.25%

Stability	
Gain drift	6 ppm/°C
Offset drift	80 μV/°C
Protection	
Overvoltage	±27 V at 25 °C

3. Range equals 10.5 V

4. Uncalibrated accuracy refers to the accuracy achieved when acquiring in raw or unscaled modes where the calibration constants stored in the module are not applied to the data.

Short-circuit	Indefinitely
---------------	--------------

**Table 2. Update Time**

Number of Channels	Update Time for NI cRIO-9151 R Series Expansion Chassis	Update Time for All Other Chassis
1	3.7 $\mu$ s minimum	3.1 $\mu$ s minimum
2	6.6 $\mu$ s minimum	5.3 $\mu$ s minimum
3	9.4 $\mu$ s minimum	7.5 $\mu$ s minimum
16	47 $\mu$ s minimum	37 $\mu$ s minimum

Noise <sup>5</sup>	500 $\mu$ V RMS
Slew rate	4 V/ $\mu$ s
Crosstalk at 1 kHz sine wave	85 dB
<b>Settling time (100 pF load, to 1 LSB)</b>	
20 V step	20 $\mu$ s
1 V step	15 $\mu$ s
0.1 V step	13 $\mu$ s
Capacity drive	1,500 pF maximum

5. The noise specification includes the glitch energy.

Monotonicity	16 bits
DNL	±1 LSB maximum
INL (endpoint)	±12 LSBs maximum
MTBF	595,509 hours at 25 °C; Bellcore Issue 2, Method 1, Case 3, Limited Part Stress Method

## NI-9264 with Spring Terminal (Black Connector) Safety Voltages

Connect only voltages that are within the following limits.

<b>Isolation</b>	
Channel-to-channel	None
<b>Channel-to-earth ground</b>	
Continuous	250 V RMS, Measurement Category II
Withstand	2,300 V RMS, verified by a 5 s dielectric withstand test

## NI-9264 with Push-In Spring Terminal (Black/Orange Connector) Safety Voltages

Connect only voltages that are within the following limits.

Channel-to-channel	None
<b>Channel-to-earth ground</b>	
Continuous	250 V RMS, Measurement Category II
Withstand up to 4,000 m	3,000 V RMS, verified by a 5 s dielectric withstand test

## NI-9264 with DSUB Safety Voltages

Connect only voltages that are within the following limits.

<b>Isolation</b>	
Channel-to-channel	None
<b>Channel-to-earth ground</b>	
Continuous	60 V DC, Measurement Category I
Withstand up to 2,000 m	1,000 V RMS, verified by a 5 s dielectric withstand test

## Measurement Category

### Measurement Category I



**Caution** Do not connect the NI-9264 with DSUB to signals or use for measurements within Measurement Categories II, III, or IV.



**Attention** Ne pas connecter le NI-9264 with DSUB à des signaux dans les



catégories de mesure II, III ou IV et ne pas l'utiliser pour effectuer des mesures dans ces catégories.



**Warning** Do not connect the NI-9264 with DSUB to signals or use for measurements within Measurement Categories II, III, or IV, or for measurements on MAINS circuits or on circuits derived from Overvoltage Category II, III, or IV which may have transient overvoltages above what the product can withstand. The product must not be connected to circuits that have a maximum voltage above the continuous working voltage, relative to earth or to other channels, or this could damage and defeat the insulation. The product can only withstand transients up to the transient overvoltage rating without breakdown or damage to the insulation. An analysis of the working voltages, loop impedances, temporary overvoltages, and transient overvoltages in the system must be conducted prior to making measurements.



**Mise en garde** Ne pas connecter le NI-9264 with DSUB à des signaux dans les catégories de mesure II, III ou IV et ne pas l'utiliser pour des mesures dans ces catégories, ou des mesures sur secteur ou sur des circuits dérivés de surtensions de catégorie II, III ou IV pouvant présenter des surtensions transitoires supérieures à ce que le produit peut supporter. Le produit ne doit pas être raccordé à des circuits ayant une tension maximale supérieure à la tension de fonctionnement continu, par rapport à la terre ou à d'autres voies, sous peine d'endommager et de compromettre l'isolation. Le produit peut tomber en panne et son isolation risque d'être endommagée si les tensions transitoires dépassent la surtension transitoire nominale. Une analyse des tensions de fonctionnement, des impédances de boucle, des surtensions temporaires et des surtensions transitoires dans le système doit être effectuée avant de procéder à des mesures.

Measurement Category I is for measurements performed on circuits not directly connected to the electrical distribution system referred to as **MAINS** voltage. MAINS is a hazardous live electrical supply system that powers equipment. This category is for measurements of voltages from specially protected secondary circuits. Such voltage measurements include signal levels, special equipment, limited-energy parts of

equipment, circuits powered by regulated low-voltage sources, and electronics.



**Note** Measurement Categories CAT I and CAT O are equivalent. These test and measurement circuits are for other circuits not intended for direct connection to the MAINS building installations of Measurement Categories CAT II, CAT III, or CAT IV.

## Measurement Category II



**Caution** Do not connect the NI-9264 with spring terminal to signals or use for measurements within Measurement Categories III or IV.



**Attention** Ne pas connecter le NI-9264 with spring terminal à des signaux dans les catégories de mesure III ou IV et ne pas l'utiliser pour effectuer des mesures dans ces catégories.

Measurement Category II is for measurements performed on circuits directly connected to the electrical distribution system. This category refers to local-level electrical distribution, such as that provided by a standard wall outlet, for example, 115 V for U.S. or 230 V for Europe.

## Environmental Characteristics

Temperature	
Operating	-40 °C to 70 °C
Storage	-40 °C to 85 °C
Humidity	
Operating	10% RH to 90% RH, noncondensing

Storage	5% RH to 95% RH, noncondensing	
Ingress protection	IP40	
Pollution Degree	2	
<b>Maximum altitude</b>		
NI-9264 with spring terminal (black connector)	2,000 m	
NI-9264 with spring terminal (push-in style, black/orange connector)	4,000 m	
NI-9264 with DSUB	2,000 m	
<b>Shock and Vibration</b>		
<b>Operating vibration</b>		
Random	5 g RMS, 10 Hz to 500 Hz	
Sinusoidal	5 g, 10 Hz to 500 Hz	
Operating shock	30 g, 11 ms half sine; 50 g, 3 ms half sine; 18 shocks at 6 orientations	

To meet these shock and vibration specifications, you must panel mount the system.

# Physical Characteristics

## Weight

NI-9264 with spring terminal (black connector)	156 g (5.5 oz)
NI-9264 with push-in spring terminal (black/orange connector)	161 g (5.7 oz)
NI-9264 with DSUB	146 g (5.2 oz)

## NI-9264 with spring terminal (Black Connector) Wiring

<b>Spring terminal wiring</b>	
Gauge	0.08 mm <sup>2</sup> to 1.0 mm <sup>2</sup> (28 AWG to 18 AWG) copper conductor wire
Wire strip length	7 mm (0.28 in.) of insulation stripped from the end
Temperature rating	90 °C minimum
Wires per spring terminal	One wire per spring terminal
<b>Connector securement</b>	
Securement type	Screw flanges provided
Torque for screw flanges	0.2 N · m (1.80 lb · in.)

## NI-9264 with Push-In Spring Terminal (Black/Orange Connector)

Push-in spring terminal wiring	
Gauge	0.14 mm <sup>2</sup> to 1.5 mm <sup>2</sup> (26 AWG to 16 AWG) copper conductor wire
Wire strip length	10 mm (0.394 in.) of insulation stripped from the end
Temperature rating	90 °C minimum
Wires per spring terminal	One wire per spring terminal; two wires per spring terminal using a 2-wire ferrule
Connector securement	
Securement type	Screw flanges provided
Torque for screw flanges	0.2 N · m (1.80 lb · in.)

## Power Requirements

Power consumption from chassis	
Active mode	1 W maximum
Sleep mode	25 μW maximum
Thermal dissipation (at 70 °C)	
Active mode	1 W maximum

Sleep mode	25 $\mu$ W maximum
------------	--------------------

## Calibration

You can obtain the calibration certificate and information about calibration services for the NI-9264 at [ni.com/calibration](https://ni.com/calibration).

Calibration interval	1 year
----------------------	--------