
cRIO-9047

Specifications

2024-08-06



Contents

cRIO-9047 Specifications..... 3

cRIO-9047 Specifications

Definitions

Warranted specifications describe the performance of a model under stated operating conditions and are covered by the model warranty.

Characteristics describe values that are relevant to the use of the model under stated operating conditions but are not covered by the model warranty.

- **Typical** specifications describe the performance met by a majority of models.
- **Nominal** specifications describe an attribute that is based on design, conformance testing, or supplemental testing.

Specifications are **Typical** unless otherwise noted.

Conditions

Specifications are valid for -40 °C to 70 °C unless otherwise noted.

Processor

CPU	Intel Atom E3940
Number of cores	4
CPU frequency	1.6 GHz (base), 1.8 GHz (burst)
On-die L2 cache	2 MB

Software



Note For minimum software support information, visit ni.com/r/SWsupport.

Supported operating system	NI Linux Real-Time (64-bit)
Supported C Series module programming modes	Real-Time (NI-DAQmx) Real-Time Scan (I/O Variables) LabVIEW FPGA
Application software	
LabVIEW	LabVIEW 2017 or later, LabVIEW Real-Time Module 2017 or later, LabVIEW FPGA Module 2017 or later



Note LabVIEW FPGA Module is not required when using Real-Time Scan (I/O Variables) mode or Real-Time (NI-DAQmx) mode. To program the user-accessible FPGA on the cRIO-9047, the LabVIEW FPGA Module is required.



Note C/C++ Development Tools for NI Linux Real-Time is an optional interface for C/C++ programming of the cRIO-9047 processor. Visit ni.com/r/RIOCdev for more information about the C/C++ Development Tools for NI Linux Real-Time. For information on setting up a C/C++ based toolchain, visit ni.com/r/NILRTCrossCompile.

Driver software	NI CompactRIO Device Drivers December 2017 or later
-----------------	---

Network/Ethernet Port

Number of ports	2
Network interface	10Base-T, 100Base-TX, and 1000Base-T Ethernet
Compatibility	IEEE 802.3
Communication rates	10 Mb/s, 100 Mb/s, 1,000 Mb/s, auto-negotiated
Maximum cabling distance	100 m/segment

Network Timing and Synchronization

Protocol	IEEE 802.1AS-2011 IEEE 1588-2008 (default end-to-end profile)
Supported Ethernet ports	Port 0, port 1
Network synchronization accuracy	<1 μ s



Note Network synchronization is system-dependent. For information about network synchronization accuracy, visit ni.com/r/criosync.



Note The cRIO-9047 employs time-aware transmission support.

RS-232 Serial Port

Maximum baud rate	115,200 b/s
Data bits	5, 6, 7, 8
Stop bits	1, 2
Parity	Odd, even, mark, space
Flow control	RTS/CTS, XON/XOFF, DTR/DSR
RI wake maximum low level	0.8 V
RI wake minimum high level	2.4 V
RI overvoltage tolerance	± 24 V

RS-485 Serial Port

Maximum baud rate	230,400 b/s
Data bits	5, 6, 7, 8
Stop bits	1, 2

Parity	Odd, even, mark, space
Flow control	XON/XOFF
Wire mode	4-wire, 2-wire, 2-wire auto
Isolation voltage	60 V DC continuous, port to earth ground




Note The RS-485 serial port ground and shield are functionally isolated from chassis ground to prevent ground loops, but do not meet IEC 61010-1 for safety isolation.




Cable requirement	Unshielded, 30 m maximum length (limited by EMC/surge)
-------------------	--



Note RS-485 is capable of 1.2 km (4,000 ft) length without surge limitation.


USB Ports

Port 1: 	
Type	USB Type-A, host port
USB interface	USB 2.0, Hi-Speed
Maximum data rate	480 Mb/s

Maximum current	900 mA
Port 2:  	
Type	USB Type-C, host port
USB interface	USB 3.1 Gen1, SuperSpeed
Maximum data rate	5 Gb/s
Maximum current	900 mA
Alternate modes	DisplayPort
Port 3: 	
Type	USB Type-C, dual role port (device or host)
USB interface	USB 3.1 Gen1, SuperSpeed
Maximum data rate	5 Gb/s
Maximum current	900 mA

DisplayPort over USB Type-C

Maximum resolution	3840 × 2160 at 60 Hz
--------------------	----------------------

Supported standard	DisplayPort 1.2
Supported USB ports	Port 2: 

SD Card Slot

SD card support	SD and SDHC standards
Supported interface speeds	UHS - I SDR50 and DDR50



Notice Full and high speed SD cards are prohibited for use with the cRIO-9047.

Memory

Nonvolatile memory (SSD)	4 GB
Nonvolatile memory (SSD) type	Planar SLC NAND



Note Visit ni.com/r/ssdbp for information about the life span of the nonvolatile memory and about best practices for using nonvolatile memory.

Volatile memory (DRAM)	
Density	4 GB

Type	DDR3L
Maximum theoretical data rate	12.8 GB/s

Reconfigurable FPGA

FPGA type	Xilinx Kintex-7 7K70T
Number of flip-flops	82,000
Number of 6-input LUTs	41,000
Number of DSP slices (18 × 25 multipliers)	240
Available block RAM	4,860 kbits
Number of DMA channels	16
Number of logical interrupts	32

Internal Real-Time Clock

Accuracy	200 ppm; 40 ppm at 25 °C
----------	--------------------------

Controller PFI 0

Maximum input or output frequency	1 MHz
Cable length	3 m (10 ft)
Cable impedance	50 Ω
PFI 0 connector	SMB
Power-on state	High impedance
I/O standard compatibility	5 V TTL
I/O voltage protection	± 30 V
Maximum operating conditions	
I_{OL} output low current	8 mA maximum
I_{OH} output high current	-8 mA maximum

Table 1. DC Input Characteristics

Voltage	Minimum	Maximum
Positive going threshold	1.43 V	2.28 V
Negative going threshold	0.86 V	1.53 V
Hysteresis	0.48 V	0.87 V

Table 2. DC Output Characteristics

Voltage	Conditions	Minimum	Maximum
High	—	—	5.25 V
	Sourcing 100 μ A	4.65 V	—
	Sourcing 2 mA	3.60 V	—
	Sourcing 3.5 mA	3.44 V	—
Low	Sinking 100 μ A	—	0.10 V
	Sinking 2 mA	—	0.64 V
	Sinking 3.5 mA	—	0.80 V

Real-Time Streaming Performance

Data throughput is dependent on the application, system, and performance of the removable storage media. For information about optimizing data throughput on the cRIO-9047, visit ni.com/r/optdata.

Data throughput from system memory to target	
SD card	40 MB/s
USB Type-C	100 MB/s

Real-Time (NI-DAQmx) Mode

The following specifications are applicable for modules and slots programmed in Real-Time (NI-DAQmx) mode. For more information about using modules in LabVIEW FPGA mode or Real-Time Scan (I/O Variables) mode, visit ni.com/r/swsupport.

Analog Input

Input FIFO size	253 samples per slot
Maximum sample rate	Determined by the C Series module or modules
Timing accuracy	50 ppm of sample rate
Timing resolution	12.5 ns
Number of channels supported	Determined by the C Series module or modules
Number of hardware-timed tasks	8



Note Maximum sample rate performance is dependent on type of installed C Series module and number of channels in the task.



Note Timing accuracy does not include group delay. For more information, refer to the documentation for each C Series module.

Analog Output

Hardware-timed tasks	
Number of hardware-timed tasks	8
Number of channels supported	
Onboard regeneration	16

Non-regeneration	Determined by the C Series module or modules	
Non-hardware-timed tasks		
Number of non-hardware-timed tasks	Determined by the C Series module or modules	
Number of channels supported	Determined by the C Series module or modules	
Maximum update rate	1.6 MS/s	



Note Streaming applications are limited by system-dependent factors and the capability of C Series modules.

Timing accuracy	50 ppm of sample rate
Timing resolution	12.5 ns
Waveform onboard regeneration FIFO	8,191 samples shared among channels used
Waveform streaming FIFO	253 samples per slot

Digital Waveform

Waveform acquisition (DI) FIFO	
Parallel modules	255 samples per slot

Serial modules	127 samples per slot
Waveform onboard regeneration (DO) FIFO	
Parallel modules	
Slots 1 to 4	2,047 samples shared among slots used
Slots 5 to 8	1,023 samples shared among slots used
Waveform streaming (DO) FIFO	
Parallel modules	255 samples per slot
Serial modules	127 samples per slot
Sample clock frequency	
Digital input	0 MHz to 10 MHz
Digital output	
ot0:6 timing engine	0 MHz to 3.5 MHz
ot7 timing engine	0 MHz to 10 MHz



Note Streaming applications are limited by system-dependent factors and the capability of C Series modules.

Timing accuracy	50 ppm
-----------------	--------

Number of digital input hardware-timed tasks	8
Number of digital output hardware-timed tasks	8

General-Purpose Counters/Timers

Number of counters/ timers	4
Resolution	32 bits
Counter measurements	Edge counting, pulse, semi-period, period, two-edge separation, pulse width
Position measurements	X1, X2, X4 quadrature encoding with Channel Z reloading; two-pulse encoding
Output applications	Pulse, pulse train with dynamic updates, frequency division, equivalent time sampling
Internal base clocks	80 MHz, 20 MHz, 13.1072 MHz, 12.8 MHz, 10 MHz, 100 kHz
External base clock frequency	0 MHz to 20 MHz
Base clock accuracy	50 ppm

Output frequency	0 MHz to 20 MHz
Inputs	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down
Routing options for inputs	Any module PFI, controller PFI, analog trigger, many internal signals
FIFO	Dedicated 127-sample FIFO

Frequency Generator

Number of channels	1
Base clocks	20 MHz, 10 MHz, 100 kHz
Divisors	1 to 16 (integers)
Base clock accuracy	50 ppm
Output	Any controller PFI or module PFI terminal

Module PFI

Functionality	Static digital input, static digital output, timing input, and timing output
---------------	--

Timing output sources	Many analog input, analog output, counter, digital input, and digital output timing signals
Timing input frequency	0 MHz to 20 MHz
Timing output frequency	0 MHz to 20 MHz



Note Actual available timing output source signals are dependent on type of installed C Series module.

Digital Triggers

Source	Any controller PFI or module PFI terminal
Polarity	Software-selectable for most signals
Analog input function	Start Trigger, Reference Trigger, Pause Trigger, Sample Clock, Sample Clock Timebase
Analog output function	Start Trigger, Pause Trigger, Sample Clock, Sample Clock Timebase
Counter/timer function	Gate, Source, HW_Arm, Aux, A, B, Z, Up_Down

Module I/O States

At power-on	Module-dependent. Refer to the documentation for each C Series module.
-------------	--

Time-Based Triggers and Timestamps

Number of time-based triggers		5
Number of timestamps		6
Analog input		
Time-based triggers	Start Trigger, Sync Pulse	
Timestamps	Start Trigger, Reference Trigger, First Sample	
Analog output		
Time-based triggers	Start Trigger, Sync Pulse	
Timestamps	Start Trigger, First Sample	
Digital input		
Time-based triggers	Start Trigger	
Timestamps	Start Trigger, Reference Trigger, First Sample	
Digital output		

Time-based triggers	Start Trigger
Timestamps	Start Trigger, First Sample
Counter/timer input	
Time-based triggers	Arm Start Trigger
Timestamps	Arm Start Trigger
Counter/timer output	
Time-based triggers	Start Trigger, Arm Start Trigger
Timestamps	Start Trigger, Arm Start Trigger

CMOS Battery

Typical battery life with power applied to power connector	10 years
Typical battery life when stored at temperatures up to 25 °C	7.8 years
Typical battery life when stored at temperatures up to 85 °C	5.4 years

Power Requirements



Note Some C Series modules have additional power requirements. For more information about C Series module power requirements, refer to the C Series

module(s) documentation.



Note Sleep mode for C Series modules is not supported in Real-Time (DAQmx) Mode.

Voltage input range (measured at the cRIO-9047 power connector)

V1	9 V to 30 V
V2	9 V to 30 V
Maximum power consumption	60 W



Note The C terminal of the power connector is functionally isolated from chassis ground to prevent ground loops, but does not meet IEC 61010-1 for safety isolation



Note The maximum power consumption specification is based on a fully populated system running a high-stress application at elevated ambient temperature and with all C Series modules and USB devices consuming the maximum allowed power.

Typical standby power consumption	3.4 W at 24 V DC input
Recommended power supply	100 W, 24 V DC
Typical leakage current from secondary power input (V2) while system is powered from primary power input (V1)	

At 9 V	0.4 mA
At 30 V	1.93 mA



Notice Do not connect V2 to a DC Mains supply or to any supply that requires a connecting cable longer than 3 m(10 ft). A DC Mains supply is a local DC electricity supply network in the infrastructure of a site or building. V1 may be connected to DC Mains.



Notice Include a switch or circuit breaker in the installation to disconnect the system from DC Mains. The switch or circuit breaker must be suitably rated, accessible, and marked as the disconnecting device for the system.

EMC ratings for inputs as described in IEC 61000	
V1	Short lines, long lines, and DC distributed networks
V2	Short lines only
Power input connector	4-position, 3.5 mm pitch, pluggable screw terminal with screw locks, Sauro CTF04BV8-AN000A

Battery Guidelines



Caution Fire, explosion, and severe burn hazard. Do not open, crush, insert improperly, recharge or disassemble the battery. Do not heat the battery or the product above 100 °C. Do not incinerate the battery or the product. Do not expose the battery contents to water. Take precautions to ensure correct polarity of the battery in the product. Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.



Attention Risque d'incendie, d'explosion et de brûlures graves. Ne pas ouvrir, écraser, recharger ou démonter la pile. Ne pas chauffer la pile ou le produit au-dessus de 100 °C. Ne pas incinérer la pile ou le produit. Éviter tout contact du contenu de la pile avec de l'eau. Prenez des précautions pour vous assurer que la polarité de la batterie dans le produit est correcte. Risque d'explosion si la pile est remplacée par un type de pile incorrect. Reportez-vous à la documentation de l'appareil sur ni.com/manuals pour obtenir des informations sur le remplacement, l'élimination et le recyclage de sa pile.



Caution The battery must be replaced by a trained service technician. Refer to the product documentation on ni.com/manuals for instructions for replacing the battery.



Attention La pile doit être remplacée par un technicien de maintenance qualifié. Reportez-vous à la documentation du produit sur ni.com/manuals pour obtenir les instructions pour changer la pile.

Battery Rating	
Manufacturer	Tadiran
Model	TLH-2450/P
Quantity	1
Cell chemistry system	Lithium Thionyl Chloride

Physical Characteristics

Weight (unloaded)	2,250 g (4 lbs, 15 oz)
-------------------	------------------------

Dimensions (unloaded)	328.8 mm × 88.1 mm × 121.2 mm (12.94 in. × 3.47 in. × 4.77 in.)
Power connector wiring	
Gauge	0.5 mm ² to 2.1 mm ² (20 AWG to 14 AWG) copper conductor wire
Wire strip length	6 mm (0.24 in.) of insulation stripped from the end
Temperature rating	85 °C
Torque for screw terminals	0.20 N · m to 0.25 N · m (1.8 lb · in. to 2.2 lb · in.)
Wires per screw terminal	One wire per screw terminal
Connector securement	
Securement type	Screw flanges provided
Torque for screw flanges	0.20 N · m to 0.25 N · m (1.8 lb · in. to 2.2 lb · in.)
Insulation rating	300 V, maximum

Safety Voltages

Connect only voltages that are below these limits.

V1 terminal to C terminal	30 V, maximum
---------------------------	---------------

V2 terminal to C terminal	30 V, maximum
Chassis ground to C terminal	30 V, maximum

Environmental Characteristics

Temperature	
Operating	-40 °C to 70 °C
Storage	-40 °C to 85 °C
Humidity	
Operating	10% RH to 90% RH, noncondensing
Storage	5% RH to 95% RH, noncondensing
Ingress protection	IP20
Pollution Degree	2
Maximum altitude	5,000 m
Shock and Vibration	
Operating vibration	
Random	5 g RMS, 10 Hz to 500 Hz

Sinusoidal	5 g, 10 Hz to 500 Hz
Operating shock	30 g, 11 ms half sine; 50 g, 3 ms half sine; 18 shocks at 6 orientations

To meet these specifications, you must mount the cRIO-9047 system directly on a flat, rigid surface as described in the user manual, affix ferrules to the ends of the terminal wires, and use retention accessories for the USB 2.0 host port (NI USB Extender Cable, 152166-xx), USB type-C ports (NI Locking USB Cables, 143556-xx; NI USB Extender Cable, 143555-xx; NI USB Display Adapters, 143557-xx or 143558-xx). All cabling should be strain-relieved near input connectors. Take care to not directionally bias cable connectors within input connectors when applying strain relief.